

# **DuoCom Q-2f**

## **Two-Node Telephone Intercom System**

### **Operating Features**

#### **Basic Features**

Intercom between two stand-alone telephone handsets.  
Intercom between a parlor speaker and a telephone handset.

#### **Advanced Features**

Automatic call initiation upon pick up of any handset.  
Call initiation with Parlor Speaker by engaging and holding call button.  
Sequential ringback tone at calling station for call progress monitoring.  
Permanent hands-free intercom link between 2 speakerphone sets as desired.  
Installation of one or more handsets at each of the two available nodes.

#### **Optional Features**

Usable with No-Dial phones and other kinds as appropriate.  
Visual indicator ports for lamps and other indicators.  
Built-in power supply for indicators.  
Programmable flash pattern for indicators.  
Wirefree install with popular 'Wireless Phone Jacks'.



### **Technical Specifications**

Power Source:  
120VAC ~ 50/60 Hz ~ 0.8A  
Output Power to Indicators:  
18VAC - 300mA  
Relay Contact Rating  
1A@30VDC  
0.3A@60VDC  
0.5A@125VAC  
Weight: 3 lbs.  
Operating Environment: 41° F - 95 ° F  
Ring Generator: 5 REN maximum  
Size: **W** 3.5 in. x **H** 6.7in. x **D** 1.5 in.  
Product code: Q-2f