

DuoCom Q-2f

Two-Node Telephone Intercom System

Operating Features

Basic Features

Intercom between two stand-alone telephone handsets.
Intercom between a parlor speaker and a telephone handset.

Advanced Features

Automatic call initiation upon pick up of any handset.
Call initiation with Parlor Speaker by engaging and holding call button.
Sequential ringback tone at calling station for call progress monitoring.
Permanent hands-free intercom link between 2 speakerphone sets as desired.
Installation of one or more handsets at each of the two available nodes.

Optional Features

Usable with No-Dial phones and other kinds as appropriate.
Visual indicator ports for lamps and other indicators.
Built-in power supply for indicators.
Programmable flash pattern for indicators.
Wirefree install with popular 'Wireless Phone Jacks'.



Technical Specifications

Power Source:
120VAC ~ 50/60 Hz ~ 0.8A
Output Power to Indicators:
18VAC - 300mA
Relay Contact Rating
1A@30VDC
0.3A@60VDC
0.5A@125VAC
Weight: 3 lbs.
Operating Environment: 41° F - 95 ° F
Ring Generator: 5 REN maximum
Size: **W** 3.5 in. x **H** 6.7in. x **D** 1.5 in.
Product code: Q-2f