

# **OmniPort Q-9**

## **Multi-Service Door Access System**

### **Operating Features**

#### **Basic Features**

Dual-function door attendant system  
Annunciator Services  
Door Release Services  
Annunciator triggerable by pushbutton, motion sensor or magnetic sensor

#### **Advanced Features**

Keylock to momentarily disable Annunciator  
Keylock to override door release button and keep the entry door free open at desired periods of time  
May work as Annunciator for 2 different entry points  
May work as Door Release Controller for 2 different entry doors  
May be used as Annunciator for 1 door and Door release Controller for another Entry Door  
Outputs for Bells, Buzzers and Strobe Lights in any combination  
Two direct outputs, which can be stepped up for more output devices as necessary  
Available in Multiple Packages to fit Specific Needs

#### **Optional Features**

Wireless Extensions available for Annunciator Push button or Attendant's Door Release button.  
Wireless Remotes or Wireless Pushbutton boxes  
Optional Entry Access Keypad



### **Technical Specifications**

Power Source:  
115VAC ~ 50/60 Hz ~ 50mA  
On-board power supply: 12VDC regulated  
Weight: 1 lbs.  
Operating Environment: 10° F - 95° F  
Work with 16VAC Transformer - 1A  
Ring Generator: 7 REN maximum  
Relay contact ratings:  
1.5A @125V AC or 15A @ 24V DC  
Bell sound level: 80 dBy  
Size:  
**W** 5 in. x **H** 4.5 in. x **D** 2 in.  
Product code: Q-9  
Made in USA