

PhoneBell Q-10f

Video Door Phone Answering System

Operating Features

Basic Features

Door-to-handset intercom with standard phone handsets.
Door intercom running on inside phone wirelines.
Call initiation with Doorbox button.
Doorbox button distinctively rings all home handsets.
Door intercom with or without dial tone service from telco.
Call waiting upon door call while phone conversation ongoing.
Call waiting upon incoming phone call during entry intercom conversation.

Advanced Features

Doorchime/video port to ring doorchime box on door entry calls.
Doorchime/video port to alternatively turn video switcher on.
Operates with doorphone at more than 2000 ft. away from main location.
Maximum of 2 outdoor intercom stations with no extra interfaces.
Each door stations wires with only one twisted pair.
Distinctive handset ring on door calls to identify calling door.
Full caller ID pass-thru to handsets.

Optional Features

Large variety of doorphone models with a variety of finishes.
Video-enabled doorphones for video monitoring (concealed miniature camera within door station).

Specifications

Power Source: 120VAC ~ 50/60 Hz ~ 0.3A
Output Power to each Doorstrike:
1A@30VDC
0.3A@60VDC
0.5A@125VAC
Doorbell/Video port - Relay Contact Rating
1A@30VDC
0.3A@60VDC
0.5A@125VAC

Power Supply for Doorstrike at AC Power Port:
0.3A max @18VAC Weight: 3 lbs.
Operating Environment: 41° F - 95° F
Intercom Mode: Self-controlled 2-way intercom
Ring Generator: 7 REN maximum
Ringer Equivalence: 0.5
Size: **W** 3.5 in. x **H** 6.7in. x **D** 1.5 in.
Product code: Q-10f

