

Ultimatoll Economy Q-16S-EX with Mini-Speakers Voice Page/Music Intercom System



Operating Features

Standard Features

Handset-to-Speaker intercom with standard handsets.
Indoor intercom with existing home phones.

Advanced Features

Indoor intercom running on inside phone wirelines (CAT5).
Easy-install tabletop mini-speakers plugging into phone jacks.
No limitation on amount of speakers.
One single twisted pair throughout the home for connection of speakers.
Answer-back capability with existing phone handsets.
Speakers with individual controls for personalized sound experience at each location.
Audio jack on each speaker to plug in headphone for private sound experience.

Optional Features

Interoperable with existing PA system (requires at least one mini-speaker to connect to PA)
Intercom on one or both channels of PA system as desired.

With addition of QX-3 module:

- . Music intercom with radio/CD source for wholehouse music background.
- . Activation/Deactivation of music from any home handset.
- . Automatic disconnection of music upon page call.
- . Source of sound (radio/CD) located close to Control box or at remote location.
- . Upgradable to Door intercom with addition of Door Speakers.

Specifications

Power Source: 120VAC ~ 50/60 Hz ~ 35mA
Controller Ring Generator: 7 REN maximum
Controller Weight: 3 lbs.
Operating Environment: 41° F - 95 ° F
Controller Size: **W** 7.187 in. x **H** 10.125 in. x **D** 2.031 in.
Required cabling: CAT5 - 2 pairs minimum

Intercom Mode: Full-Duplex
Speaker connection: plugs for phone jack & power line
Speaker type: table top - monoaural
Speaker size: 2.5 in x 6.3 in. X 3.8 in.
Total Power output: 7.5W per speaker
Product code: Q-16S-EX